

# Terma MOA Operating Guide

## Decreasing Temperature

After the temperature change the appropriate number of lights will start blinking. The last light shining continuously indicates the set temperature.

The last blinking light indicates the current temperature.

## Increasing Temperature


After the temperature change one or more lights will start blinking. The last blinking light indicates the set temperature, whilst the last light that shines constantly, indicates the current temperature. The remaining lights will start shining constantly on reaching the subsequent temperature levels.

## Set Temperature Indicator

## 2 Hour Function Indicator

## 2 Hour Function

The 2 Hour button has 2 functions:

1. During the standard operation press  once and choose required temperature setting (+/-) After 2 hours the device will revert back to its previously set temperature.

2. If device is off MOA can be switched on by pressing the timer button. It will then automatically turn off after 2 hours.

Press the dryer button at any time to exit timer mode.

## On/Off Button

Turning the device on with the button will result in the radiator heating up to the set temperature. After reaching the set temperature the device will turn off and on regularly in order to maintain the set temperature.



## Frost Protection

When the liquid inside the towel rail drops below 6°C the element will switch on automatically. This is indicated by the blinking middle light.